



**EXHIBIT OSS – 63**

**Pre-Order to Firm Order Mapping Matrix**

# **Pre-Order to Firm Order Mapping Matrix**

**Network Services – Customer  
Services**

## **Copyright**

February, 2001

© BellSouth

Toni Addison  
4049274305

## Contents

---

Subject	Page
<b>Objective &amp; Introduction</b>	<b>vii</b>
Purpose	vii
Audience	vii
Introduction	vii
Version Information	viii
<b>1. Matrix Column Definitions and Sources of Mapping</b>	<b>1</b>
1.1 Matrix Column Definitions and Sources of Mapping	1
<b>2. Pre-Order to Firm-Order Mapping Matrix</b>	<b>3</b>
2.1 Single Address Match Response	3
2.1.1 AVR Message	3
2.1.2 Service Address Information	3
2.1.3 Service AddressTN Information	3
2.1.4 Service Instruction Information	3
2.1.5 Service Restriction Information	4
2.1.6 Wire Center Information	4
2.2 No Address Verified Response (AVR)	4
2.2.1 AVR Message	4
2.3 Community Names Menu Response (AVR)	4
2.3.1 AVR Message	4
2.3.2 Community Information	4
2.4 Street Name Response (AVR)	5
2.4.1 AVR Message	5
2.4.2 Street Information	5
2.5 Descriptive Name Menu Response (AVR)	5
2.5.1 AVR Message	5
2.5.2 Descriptive Name Information	5
2.6 House Numbers Response (AVR)	6
2.6.1 AVR Message	6
2.6.2 Street Range Information	6
2.7 Location Standards Response (AVR)	6
2.7.1 AVR Message	6
2.7.2 Location Standards — Address Pattern	7
2.8 Supplemental Address Response (AVR)	7
2.8.1 AVR Message	7
2.8.2 Supplemental Information	7
2.9 Basic Descriptive Address Response (AVR)	7
2.9.1 AVR Message	7

---

2.9.2	Basic Address Information	8
2.10	Basic Address Menu Response (AVR)	8
2.10.1	AVR Message	8
2.10.2	Basic Address Information	8
2.11	GSG Summary Response (AVR)	9
2.11.1	AVR Message	9
2.11.2	Community Information	9
2.11.3	Geographic Segment Information	9
2.12	Menu of Address Telephones Response (AVR)	9
2.12.1	AVR Message	9
2.12.2	Service Address Information	10
2.13	Living Units on Street Response (AVR)	10
2.13.1	AVR Message	10
2.13.2	Service Address Information	10
2.14	Telephone Number Availability Response (TNAR-TN)	11
2.14.1	TNAR-TN Message	11
2.15	Multiline Hunt Telephone Number Availability Response (TNAR-MLH)	11
2.15.1	TNAR-MLH Message	11
2.16	Direct Inward Dial Telephone Number Availability Response (TNAR-DID)	12
2.16.1	TNAR-DID Message	12
2.16.2	DID Request Detail	12
2.17	Telephone Number Availability Response for Miscellaneous Account Number (TNAR-MISC)	12
2.17.1	TNAR-MISC Message	12
2.18	Telephone Number Selection Response (TNAR-SQ)	12
2.18.1	TNAR-SQ Message	12
2.19	Cancellation Response (TNAR-CAN)	13
2.19.1	TNAR-CAN Message	13
2.20	Service Availability Response (SAR)	13
2.20.1	SAR Message	13
2.20.2	Switch Information	13
2.20.3	Detail Product & Feature Information	13
2.20.4	Product & Feature USOCs	14
2.20.5	Detail Carrier Information	14
2.21	Appointment Availability Response (SAAR)	14
2.21.1	AAR Message	14
2.21.2	CO Appointment Availability Info	14
2.21.3	PV Appointment Availability Info	14
2.21.4	Detail Appointment Interval Info	15
2.21.5	Detail Appointment Unavailability Info	15
2.22	Customer Service Record Response (CSRR)	15
2.22.1	CSRR Message	15
2.22.2	Customer Record Info	15
2.23	Calculate Due Date Response (CSRR)	16

2.23.1	CDD Response . . . . .	16
<b>3.</b>	<b>Pre-Order Response Field . . . . .</b>	<b>17</b>
3.1	Pre-Order Response Field . . . . .	17
<b>Appendix A.</b>	<b>Scenario's . . . . .</b>	<b>95</b>
A.1	Scenario #1 – REQ TYP: M; ACT: C; Description: Change activity on residence port loop service adding block . . . . .	95
A.2	Scenario #2 – REQ TYP: M; ACT: C; Description: Change activity to port loop business service with phone number change and no transfer of calls . . . . .	96
A.3	Scenario #3 – REQ TYP: M; ACT: C; Description: Change activity on residential port loop service deleting block, changing PIC, and adding PIC freeze . . . . .	98
A.4	Scenario #4 – REQ TYP: M; ACT: N; Description: New installation of port loop combo residence service with block and working service on premises (WSOP) . . . . .	99
A.5	Scenario #5 – REQ TYP: M; ACT: V; Description: Full conversion from multiline resale/retail account to port loop combo service; features are being added and/or deleted . . . . .	101
A.6	Scenario #6 – REQ TYP: M; ACT: V; Description: Full conversion from resale/retail account to port loop combo with block choices, “No Collect,” and no directory assistance call completion . . . . .	104
A.7	. . . . .	106





## Objective & Introduction

### Purpose

This document provides a mapping of pre-order response fields to firm order fields and their corresponding forms. The pre-order response fields have been extracted from the BellSouth Pre-Order Business Rules Ver 9.0 document dated November 9, 2000. This field mapping is for ALL REQTYPES.

### Audience

The intended audiences are the users of BellSouth's Pre-Order Systems.

### Introduction

The purpose of this document is to provide a mapping matrix for Competitive Local Exchange Carriers (CLECs) that submit pre-orders and firm orders electronically and/or manually to BellSouth. It outlines the various pre-order response transactions, defines each field in each system within that response (see "Matrix Column Definitions" tab for more information), and maps them to the corresponding firm order field and form where applicable.

A brief synopsis of each pre-order response is as follows:

- **Address Validation Responses (AVR)**— The AVRs provide verification of the living unit's address, either as derived from a ten digit telephone number or a customer address.
- **Telephone Number Assignment Responses (TNAR)**— The TNARs provide the CLEC with the ability to select / reserve telephone numbers.

**Note:** The TNAR — **DID** (Direct Inward Dialing) will **NOT** be covered as it is not used with the UNEP product.

- **Appointment Availability Response (AAR)**— The AAR allows CLECs to view BellSouth's Central Office, Installation, and Maintenance calendar when coordinating installation of service.
- **Service Availability Response (SAR)**— The SAR allows CLECs to obtain service and feature availability and information on the BellSouth switches. It also allows CLECs to obtain PIC information.
- **Customer Service Record Response (CSRR)**— The CSRR allows CLECs to view customer records.
- **Calculate Due Date Response (CDDR)**— The CDDR allows CLECs to view what due date BellSouth will have a service completed.

This document does **NOT** provide information regarding if a particular field is conditional, optional, required, or prohibited. For this information, please consult the "BellSouth Pre-Order Business Rules".

Please note the appendix to this document, Appendix A – Examples of Pre-Order to Firm-Order Mapping for UNEP. This document contains six (6) different ordering scenarios and how the Pre-Order fields map to the Firm-Order fields when available. The scenarios contain example data.

## **Version Information**

**Table A Revision History**

<b>Chapter</b>	<b>Date/Issue</b>	<b>Description</b>
All	March 23, 2001 / 1	Initial Issue - For version information of each system involved in the mapping (i.e. TAG), please see the "Matrix Column Definitions" tab.

## 1. Matrix Column Definitions and Sources of Mapping

### 1.1 Matrix Column Definitions and Sources of Mapping

**Table B Definitions and Sources of Mapping**

Column	Description	Source
ST Pre-Order Response Field	The name of the pre-order response field as described by BellSouth.	"BellSouth Pre-Order Business Rules" Ver 9.0 document dated November 9, 2000
ST PO Field Attr	The pre-order response field format and length as described by BellSouth.	"BellSouth Pre-Order Business Rules" Ver 9.0 document dated November 9, 2000
ST CORBA/TAG PO Response Field	The name of the pre-order response field as described by BellSouth for their CORBA gateway, TAG.	"Telecommunications Access Gateway (TAG) AP Reference Guide" Release 7.5.0.10 document dated December, 2000
ST CORBA PO Field Attr	The pre-order response field format and length as described by BellSouth for their CORBA gateway, TAG	The TAG field attributes match those of the BST field attributes.
Description	The description of the field as depicted by the Ordering and Billing Forum. If the field is not found in the Ordering and Billing Forum, the description is as depicted by BellSouth.	LSOG4, April 9, 1999; "Pre-Order Inquiry Process (POINQP) "Transaction Guide" and "Local Customer Service Inquiry (CSI) Preparation Guide" or "BellSouth Pre-Order Business Rules" Ver 9.0 document dated November 9, 2000
ST Firm Order Form	The name of the firm order form(s) on which the field is used, as defined by BellSouth.	"BellSouth Business Rules for Local Ordering - OSS99" Ver 9K document dated December 22, 2000
ST Firm Order Field	The name of the firm order field as described by BellSouth	"BellSouth Business Rules for Local Ordering - OSS99" Ver 9K document dated December 22, 2000
ST Firm Order Field Attr	The firm order field format and length as described by BellSouth.	"BellSouth Business Rules for Local Ordering - OSS99" Ver 9K document dated December 22, 2000
ST CORBA/TAG Order Field	The name of the order field as described by BellSouth for the TAG CORBA gateway.	"Telecommunications Access Gateway (TAG) AP Reference Guide" Release 7.5.0.10 document dated December, 2000
ST CORBA Order Field Attr	The order field format and length as described by BellSouth for the TAG CORBA gateway.	"Telecommunications Access Gateway (TAG) AP Reference Guide" Release 7.5.0.10 document dated December, 2000

- continued -

**Table B Definitions and Sources of Mapping (continued)**

ST EDI Firm Order Field	<p>The name of the firm order field as described by BellSouth for the EDI specifications.</p> <p><b>Note:</b> This document does not contain EDI field attribute information because EDI field lengths will be truncated as a result of BellSouth ordering systems field length requirements.</p>	"BellSouth EDI Specifications Guide - TCIF 9" document dated October 30, 2000
omments	Additional notes pertaining to the field.	Various

## 2. Pre-Order to Firm-Order Mapping Matrix

### 2.1 Single Address Match Response

#### 2.1.1 AVR Message

AVR Message	
INQ-NUM	MSG-ID
MSG-TEXT	

#### 2.1.2 Service Address Information

Service Address Information		
HOUSE-NUM	STRUC-BLDG	STATE
HOUSE-NUM-SUFFIX	ELEV-FLOOR	ZIP-CODE
STREET-NAME1	UNIT-ROOM	XBOUND-STATE
STREET-DIR	ROUTE	RATE-ZONE
THOROUGHFARE	BOX	DRIVE-INSTRUCTIONS
STREET-SUFFIX	CITY	ICO-IND
DESC-LOC		

#### 2.1.3 Service AddressTN Information

Service Address TN Information	
TN	ADDR-STATUS
QUICK-SERV-IND	FACAVAIL

#### 2.1.4 Service Instruction Information

Service Instruction Information
SERVICE-INSTRUC-TEXT

### 2.1.5 Service Restriction Information

Service Restriction Information	
EST-SERVICE-DATE	TEXT-CODE
TEXT	

### 2.1.6 Wire Center Information

Wire Center Information		
LST	AREA-TRANS-CUT-DT	AREA-TRANS-NPANXX
LSO-NPA-TTA	AREA-TRANS-NUM-CHG/DT	TARIFF-EXCHANGE-CODE

## 2.2 No Address Verified Response (AVR)

### 2.2.1 AVR Message

AVR Message	
INQ-NUM	MSG-ID
MSG-TEXT	CITY
XBOUND-STATE	

## 2.3 Community Names Menu Response (AVR)

### 2.3.1 AVR Message

AVR Message	
INQ-NUM	MSG-ID
MSG-TEXT	

### 2.3.2 Community Information

Community Information	
CITY	ZIP-CODE
STATE	XBOUND-STATE

## 2.4 Street Name Response (AVR)

### 2.4.1 AVR Message

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	

### 2.4.2 Street Information

Street Information	
HOUSE-NUM-HI	THOROUGHFARE
HOUSE-NUM-LOW	STREET-SUFFIX
ODD-EVEN-IND	CITY
AHN-STATUS	STATE
STREET-NAME1	XBOUND-STATE
STREET-DIR	

## 2.5 Descriptive Name Menu Response (AVR)

### 2.5.1 AVR Message

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	

### 2.5.2 Descriptive Name Information

Descriptive Name Information	
CITY	XBOUND-STATE
STATE	DESC-LOC

## 2.6 House Numbers Response (AVR)

### 2.6.1 AVR Message

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	STREET-NAME1
STREET-DIR	THOROUGHFARE
STREET-SUFFIX	CITY
STATE	XBOUND-STATE

### 2.6.2 Street Range Information

Street Range Information	
HOUSE-NUM-HI	ODD-EVEN-IND
HOUSE-NUM-LOW	AHN-STATUS

## 2.7 Location Standards Response (AVR)

### 2.7.1 AVR Message

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	HOUSE-NUM
HOUSE-NUM-SUFFIX	STREET-NAME1
STREET-DIR	THOROUGHFARE
STREET-SUFFIX	ROUTE
BOX	CITY
STATE	XBOUND-STATE
DESC-LOC	



**2.7.2 Location Standards — Address Pattern**

Location Standards — Address Pattern	
STRUC-BLDG	UNIT-ROOM
ELEV-FLOOR	

**2.8 Supplemental Address Response (AVR)**

**2.8.1 AVR Message**

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	HOUSE-NUM
HOUSE-NUM-SUFFIX	STREET-NAME1
STREET-DIR	THOROUGHFARE
STREET-SUFFIX	ROUTE
BOX	CITY
STATE	XBOUND-STATE
DESC-LOC	

**2.8.2 Supplemental Information**

Supplemental Information	
STRUC-BLDG	TN
ELEV-FLOOR	ADDR-STATUS
UNIT-ROOM	

**2.9 Basic Descriptive Address Response (AVR)**

**2.9.1 AVR Message**

AVR Message	
INQ-NUM	MSG-TEXT
MSG-ID	

**2.9.2 Basic Address Information**

<b>Basic Address Information</b>	
HOUSE-NUM	ROUTE
HOUSE-NUM-SUFFIX	BOX
STRUC-BLDG	CITY
ELEV-FLOOR	STATE
UNIT-ROOM	XBOUND-STATE
STREET-NAME1	DRIVE-INSTRUCTIONS
STREET-DIR	TN
THOROUGHFARE	ADDR-STATUS
STREET-SUFFIX	

**2.10 Basic Address Menu Response (AVR)**

**2.10.1 AVR Message**

<b>AVR Message</b>	
INQ-NUM	MSG-TEXT
MSG-ID	

**2.10.2 Basic Address Information**

<b>Basic Address Information</b>	
HOUSE-NUM	ROUTE
HOUSE-NUM-SUFFIX	BOX
STRUC-BLDG	CITY
ELEV-FLOOR	STATE
UNIT-ROOM	XBOUND-STATE
STREET-NAME1	DRIVE-INSTRUCTIONS
STREET-DIR	TN

- continued -

- continued -

THOROUGHFARE	ADDR-STATUS
STREET-SUFFIX	DESC-LOC

**2.11 GSG Summary Response (AVR)**

**2.11.1 AVR Message**

<b>AVR Message</b>	
INQ-NUM	MSG-TEXT
MSG-ID	STREET-NAME1
STREET-DIR	THOROUGHFARE
STREET-SUFFIX	

**2.11.2 Community Information**

<b>Community Information</b>	
CITY	XBOUND-STATE
STATE	

**2.11.3 Geographic Segment Information**

<b>Geographic Segment Information</b>	
ZIP-CODE	HOUSE-NUM-LOW
LST	ODD-EVEN-IND
LSO-NPA-TTA	AHN-STATUS
HOUSE-NUM-HI	RATE-ZONE

**2.12 Menu of Address Telephones Response (AVR)**

**2.12.1 AVR Message**

<b>AVR Message</b>	
INQ-NUM	MSG-TEXT
MSG-ID	TN

**2.12.2 Service Address Information**

<b>Service Address Information</b>	
HOUSE-NUM	STREET-SUFFIX
HOUSE-NUM-SUFFIX	ROUTE
STRUC-BLDG	BOX
ELEV-FLOOR	CITY
UNIT-ROOM	STATE
STREET-NAME1	DRIVE-INSTRUCTIONS
STREET-DIR	ADDR-STATUS
THOROUGHFARE	

**2.13 Living Units on Street Response (AVR)**

**2.13.1 AVR Message**

<b>AVR Message</b>	
INQ-NUM	MSG-TEXT
MSG-ID	

**2.13.2 Service Address Information**

<b>Service Address Information</b>	
HOUSE-NUM	BOX
HOUSE-NUM-SUFFIX	CITY
STRUC-BLDG	STATE
ELEV-FLOOR	XBOUND-STATE
UNIT-ROOM	TN
STREET-NAME1	HOUSE-NUM-HI
STREET-DIR	HOUSE-NUM-LOW
THOROUGHFARE	ODD-EVEN-IND

- continued -

- continued -

STREET-SUFFIX	AHN-STATUS
ROUTE	DRIVE-INSTRUCTIONS

## 2.14 Telephone Number Availability Response (TNAR-TN)

### 2.14.1 TNAR-TN Message

<b>TNAR-TN Message</b>	
INQ-NUM	TN-OPT-SEQLINE
MSG-ID	TN-OPT-ASCCON
MSG-TEXT	TN-OPT-DSCCON
QTY-PROVIDED	TN-OPT-IDENT
CONFIRM-NUM	LST
TN-OPT-EASY	REQNUM
TN-OPT-COIN	

## 2.15 Multiline Hunt Telephone Number Availability Response (TNAR-MLH)

### 2.15.1 TNAR-MLH Message

<b>TNAR-MLH Message</b>	
INQ-NUM	LST
MSG-ID	HUNT-GRP-NUM1
MSG-TEXT	IN-TER-RANGE1
CONFIRM-NUM	OUT-TER-RANGE1
LEAD-TN	MLGH-LEAD-TN1
QTY-IN-TER	HUNT-GRP-NUM2
QTY-OUT-TER	IN-TER-RANGE2
EXIST-MLH-NO	OUT-TER-RANGE2
LAST-IN-TER	MLGH-LEAD-TN2
LAST-OUT-TER	

## 2.16 Direct Inward Dial Telephone Number Availability Response (TNAR-DID)

### 2.16.1 TNAR-DID Message

TNAR-DID Message	
INQ-NUM	LST
MSG-ID	CONFIRM-NUM
MSG-TEXT	QTY-PROVIDED

### 2.16.2 DID Request Detail

DID-Range
-----------

## 2.17 Telephone Number Availability Response for Miscellaneous Account Number (TNAR-MISC)

### 2.17.1 TNAR-MISC Message

TNAR-MISC Message	
INQ-NUM	QTY-PROVIDED
MSG-ID	CONFIRM-NUM
MSG-TEXT	REQNUM
BST-NPA-NXX	

## 2.18 Telephone Number Selection Response (TNAR-SQ)

### 2.18.1 TNAR-SQ Message

TNAR-SQ Message	
INQ-NUM	LST
MSG-ID	CONFIRM-NUM
MSG-TEXT	

## 2.19 Cancellation Response (TNAR-CAN)

### 2.19.1 TNAR-CAN Message

TNAR-CAN Message	
INQ-NUM	MSG-TEXT
MSG-ID	LST

## 2.20 Service Availability Response (SAR)

### 2.20.1 SAR Message

SAR Message	
INQ-NUM	MSG-TEXT
MSG-ID	

### 2.20.2 Switch Information

Switch Information	
LST	BST-NPA-NXX
LSO-NPA-TTA	800-SERV-OFF
SWITCH-TYPE	WATS-SERV-OFF
ISDN-IND	CLLI

### 2.20.3 Detail Product & Feature Information

Detail Product & Feature Information	
PRODUCT-ID	AN
PRODUCT-NAME	TARIFF-NOTES
FEATURE-TITLE	TARIFF-STATUS
COFA	TARIFF-EFF-DT
EFF-DT	

**2.20.4 Product & Feature USOCs**

Product & Feature USOCs	
EXT-FEATURE-NAME	USOC

**2.20.5 Detail Carrier Information**

Detail Carrier Information	
CIC	ACNA
TOSOFG	ACC-CARRIER-TN
ACC-CARRIER-NAME	

**2.21 Appointment Availability Response (SAAR)**

**2.21.1 AAR Message**

AAR Message	
INQ-NUM	MSG-TEXT
MSG-ID	

**2.21.2 CO Appointment Availability Info**

CO Appointment Availability Info	
CO-MON1	CO-FRI1
CO-TUES1	CO-SAT1
CO-WED1	CO-SUN1
CO-THU1	

**2.21.3 PV Appointment Availability Info**

PV Appointment Availability Info	
PV-MON1	PV-FRI1
PV-TUE1	PV-SAT1
PV-WED1	PV-SUN1
PV-THU1	



**2.21.4 Detail Appointment Interval Info**

<b>Detail Appointment Interval Info</b>	
PV-REINST	NEWINST11-15
REINST-3	ADDLINE
NEWINST1-2	RES-IW
NEWINST3	PV-REINST-BUS
NEWINST4	NEWINST1-2-BUS
NEWINST5	BUS-IW
NEWINST6-10	QUICK-SERVICE

**2.21.5 Detail Appointment Unavailability Info**

<b>Detail Appointment Unavailability Info</b>	
DATE-QUAL	CLOSE-REASCD1
DATE	CLOSE-REASCD2

**2.22 Customer Service Record Response (CSRR)**

**2.22.1 CSRR Message**

<b>CSRR Message</b>	
INQ-NUM	CUS-CODE
ATN	MSG-ID
MSG-TEXT	

**2.22.2 Customer Record Info**

<b>Customer Record Info</b>	
CSR-TEXT1	CSR-TEXT9
CSR-TEXT2	CSR-TEXT10
CSR-TEXT3	CSR-TEXT11
CSR-TEXT4	CSR-TEXT12
CSR-TEXT5	CSR-TEXT13

- continued -

CSR-TEXT6	CSR-TEXT14
CSR-TEXT7	CSR-TEXT15
CSR-TEXT8	

## 2.23 Calculate Due Date Response (CSRR)

### 2.23.1 CDD Response

<b>CDD Response</b>	
DUE DATE	MSG-TEXT
MSG-ID	

### 3. Pre-Order Response Field

#### 3.1 Pre-Order Response Field

To return to previous location, click the back button.

##### 800 SERV-OFF

BST PO Field Attr	11 A/N
BST CORBA/TAG PO Response Field	SwitchInfo::eightHundredServingOffice
BST TAG PO Field Attr	11 A/N
Description	800 Serving Office — identifies if the switch is an 800 switch
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	

##### ACC-CARRIER-NAME

BST PO Field Attr	50 A/N
BST CORBA/TAG PO Response Field	CarrierInfo::accessCarrierName
BST TAG PO Field Attr	50 A/N
Description	Access Carrier Name — identifies the name of the access carrier
BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ACC-CARRIER-TN**

BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	CarrierInfo::accessCarrierTelephoneNumber
BST TAG PO Field Attr	10 A/N
Description	Access Carrier Telephone Number — identifies the contact number for the access carrier
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ACNA**

BST PO Field Attr	3 A/N
BST CORBA/TAG PO Response Field	CarrierInfo::accessCarrierNameAbbreviation
BST TAG PO Field Attr	3 A/N
Description	Access Carrier Name Abbreviation — Identifies the abbreviation of the access carrier
BST Firm Order Form	N/A

BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ADDLINE**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::addLine
BST TAG PO Field Attr	2 A/N

Description Add Line Interval — Add Line Interval — Interval to add 1 new residential line

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ADDR-STATUS**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	ServiceAddressTelephoneInfo::addressStatus
BST TAG PO Field Attr	2 A/N

Description Telephone Number Status Code — status of a given telephone number at the specified address

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**AHN-STATUS**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	assignedHouseNumberStatus
BST TAG PO Field Attr	1 A/N

Description Assigned House Number Status — provides status on fictional house number addresses for BST house number assignments

BST Firm Order Form	N/A
BST Firm Order Field	SANO?
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**AN**

BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::accessNumber
BST TAG PO Field Attr	10 A/N

Description Access Number — identifies the access number associated with a feature

BST Firm Order Form N/A  
 BST Firm Order Field N/A  
 BST Firm Order Field Attr N/A  
 BST CORBA/TAG Order Field N/A  
 BST TAG Order Field Attr N/A  
 BST EDI Firm Order Field N/A

Comments

**AREA-TRANS-CUT-DT**

BST PO Field Attr 8 N  
 BST CORBA/TAG PO Response Field AreaTransferInfo::areaTransferCutDate  
 BST TAG PO Field Attr 8 N

Description Area Transfer Cut Date — actual area transfer cut date when new customers in the old wire center are assigned a telephone number from the new wire split (i.e. NPA split)

BST Firm Order Form N/A  
 BST Firm Order Field N/A  
 BSTI Firm Order Field Attr N/A  
 BST CORBA/TAG Order Field N/A  
 BST TAG Firm Order Field N/A  
 BST EDI Firm Order Field N/A

Comments CCYYMMDD

**AREA-TRANS-NUM-CHG-DT**

BST PO Field Attr	8 N
BST CORBA/TAG PO Response Field	AreaTransferInfo::areaTransferNumChgDate
BST TAG PO Field Attr	8 N
Description	Area Transfer Number Change Date — date often of the actual area transfer cut date when new customers in the old wire center are assigned a telephone number from the new wire center even though they are still physically within the old wire center area(i.e. NPA split)
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	CCYYMMDD

**AREA-TRANS-NPANXX**

BST PO Field Attr	6 N
BST CORBA/TAG PO Response Field	AreaTransferInfo2/8/20012/8/2001 areaTransferNpaNxx
BST TAG PO Field Attr	6 N
Description	Area Transfer NPANXX — contains the NPANXX of the wire center to which the specified address will be transferred (i.e. NPA split)
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A



BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>ATN</b>	
BST PO Field Attr	40 A/N
BST CORBA/TAG PO Response Field	CustomerRequest::accountTelephoneNumber
BST CORBA PO Field Attr	40 A/N
Description	Account Telephone Number — identifies the account (billing) telephone number of the end user
BST Firm Order Form	<ul style="list-style-type: none"><li>• LSR</li><li>• LSR-HGI</li><li>• EU</li><li>• DL</li><li>• DSCR</li><li>• LS</li><li>• LSNP</li><li>• NP</li><li>• RS</li><li>• PS</li></ul>
BST Firm Order Field	ATN ***See note
BST Firm Order Field Attr	manual: 12 N with 2 preprinted hyphens electronic: 10 N
BST CORBA/TAG Order Field	LSR::atn***See note
BST TAG Order Field Attr	10 A/N

BST EDI Firm Order Field	ATN***See Note
Comments	The pre-order field ATN doesn't always map to the firm order field ATN. If the order is a change or migrate to an existing account, the old ATN, not the ATN from the pre-order response, would be used in this firm order ATN field.

**BOX**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	Address::postalBox
BST TAG PO Field Attr	8 A/N
Description	Post Office Box — identifies the post office box of the end user's location
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	

**BST-NPA-NXX**

BST PO Field Attr	6 A/N
BST CORBA/TAG PO Response Field	AlternativeAddressInfo::npanxx
BST TAG PO Field Attr	6 A/N
Description	BST NPANXX — identifies the miscellaneous NPANXXs available for the specified location
BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**BUS-IW**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::businessInsideWire
BST TAG PO Field Attr	2 A/N

Description Business Inside Wire Interval — Interval for business unregulated, inside wire, other

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CIC**

BST PO Field Attr	4 N
BST CORBA/TAG PO Response Field	CarrierInfo::cic
BST TAG PO Field Attr	4 N

Description PIC/LPIC — identifies the PIC/LPIC of the carrier

BST Firm Order Form	N/A
---------------------	-----

BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CITY**

BST PO Field Attr	32 A/N
BST CORBA/TAG PO Response Field	Address::city
BST TAG PO Field Attr	32 A/N
Description	Service Address Locality — identifies the city of community where the service is located (i.e. “Concord”)
BST Firm Order Form	EU
BST Firm Order Field	EU-CITY
BST Firm Order Field Attr	Manual: 35 A/N Electronic: 25 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::euCity
BST TAG Order Field Attr	25A/N
BST EDI Firm Order Field	CITY-EU

Comments

**CLLI**

BST PO Field Attr	11 A/N
BST CORBA/TAG PO Response Field	SwitchInfo::switchCliList
BSTTAG PO Field Attr	11A/N
Description	Alternate Service CLLI — identifies other alternative CLLIs found in the same central office

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CLOSE-REASCD1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	CloseDate::reasonCode1
BST TAG PO Field Attr	1 A/N

Description Closed Reason Code1 — identifies the code of the reason for being closed

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CLOSE-REASCD2**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	CloseDate::reasonCode2
BST TAG PO Field Attr	1 A/N

Description	Closed Reason Code 2 — identifies the code of the reason for being closed
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**COFA**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::centralOfficeFeatureAvail
BST TAG PO Field Attr	2 A/N

Description Central Office Feature Availability — identifies the overall service status of the feature

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CO-FRI1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability

BST TAG PO Field Attr	1 A/N
Description	CO Appointment Availability Status Code for FRI1 — provides central office availability for Friday
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CO-MON1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N
Description	CO Appointment Availability Status Code for MON1 — provides central office availability for Monday
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	NA/
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
<b>CONFIRM-NUM</b>	
BST PO Field Attr	7 A/N
BST CORBA/TAG PO Response Field	ConfirmationNumber
BST TAG PO Field Attr	7 A/N
Description	Confirmation Number — identifies the confirmation number of the telephone number(s) returned on a successful telephone number selection/reservation response
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>CO-THU1</b>	
BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N
Description	CO Appointment Availability Status Code for THU1 — provides central office availability for Thursday
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A



BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CO-TUES1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N

Description	CO Appointment Availability Status Code for TUE1 — provides central office availability for Tuesday
-------------	---

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CO-WED1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N

Description	CO Appointment Availability Status Code for WED1 — provides central office availability for Wednesday
-------------	---

BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CO-SAT1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N

Description CO Appointment Availability Status Code for SAT1 — provides central office availability for Saturday

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDIFirm Order Field	N/A

Comments

**CO-SUN1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::coAvailability
BST TAG PO Field Attr	1 A/N

Description CO Appointment Availability Status Code for SUN1 — provides central office availability for Sunday

BSTFirm Order Form	N/A
--------------------	-----

BSTFirm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**CSR-TEXT1**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BSTTAG PO Field Attr	49 A/N

Description Customer Record Data is returned for a successful query and populated with information on the customer record requested

BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT2**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT3**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAGA PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BSTFirm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT4**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to the order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT5**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT6**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAGA PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT7**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT8**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT9**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT10**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BSTFirm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A



BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT11**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT12**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDIFirm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT13**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N

Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT14**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to the order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CSR-TEXT15**

BST PO Field Attr	49 A/N
BST CORBA/TAG PO Response Field	customerTextList
BST TAG PO Field Attr	49 A/N
Description	Customer Record Data is returned for a successful query and populated with information on the customer record requested
BST Firm Order Form	*see comment below
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Note: this only maps to te order when the result is the result of a request by CKTID; in that case, only one 13 A/N field is returned, which contains the AN

**CUS-CODE**

BST PO Field Attr	3 A/N
BST CORBA/TAG PO Response Field	CustomerRequest::customerCode
BST TAGA PO Field Attr	3 A/N
Description	Customer Code — identifies the customer code found on the customer record
BST Firm Order Form	<ul style="list-style-type: none"> <li>• LSR</li> <li>• LSR-HGI</li> <li>• EU</li> <li>• DL</li> <li>• DSCR</li> <li>• LS</li> <li>• LSNP</li> <li>• NP</li> <li>• RS</li> <li>• PS</li> </ul>
BST Firm Order Field	CHAR 11–13 OF ATN
BST Firm Order Field Attr	manual: up to 20 A/N
BST CORBA/TAG Order Field	char 11–13 of LSR::an
BST TAG Order Field Attr	3 A/N

BST EDI Firm Order Field char 11–13 of ATN

Comments

**DATE**

BST PO Field Attr 8 N

BST CORBA/TAG PO Response Field CloseDate::closeDates

BST TAG PO Field Attr 8 N

Description Date — Closed or holiday date

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**DATE-QUAL**

BST PO Field Attr 3 A/N

BST CORBA/TAG PO Response Field AppointmentData::holidays

BST TAG PO Field Attr 3 A/N

Description Date-Qualifier — holiday dates are dates specified as BST official company holiday. No appointment dates are to be assigned on these days. Dates returned are those after today's date.

BST Firm Order Form N/A

BST FirmOrder Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**DESC-LOC**

BST PO Field Attr	50 A/N
BST CORBA/TAG PO Response Field	Address::DescriptiveLocation
BST TAG PO Field Attr	50 A/N
Description	Service Address Descriptive Location — identifies additional location information about the service address
BST Firm Order Form	EU
BST Firm Order Field	SADLO (see commenta)
BST Firm Order Field Attr	100 A/N
BST CORBA/TAG Order Field	lsr::SADLO (see comments)
BST TAG Order Field Attr	100 A/N
BST EDI Firm Order Field	SADLO (see comments)

Comments

SADLO is a concatenation of  
SERVICE-INSTRUC-TEXT + DRIVE-  
INSTRUCTIONS + DESC-LOC

**DID-RANGE**

BST PO Field Attr	40 A/N
BST CORBA/TAG PO Response Field	TelephoneNumberRange::highValue — TelephoneNumberRange::lowValue
BST TAG PO Field Attr	40 A/N
Description	DID Range — identifies the DID range of telephone numbers

BST Firm Order Form	DRS
BST Firm Order Field	DTNR
BST Firm Order Field Attr	Manual: 17 A/N including 3 preprinted hyphens: electronic: up to 15 A/N
BST CORBA/TAG Order Field	15
BST TAG Order Field Attr	
BST EDI Firm Order Field	
Comments	

**DRIVE-INSTRUCTIONS**

BST PO Field Attr	175 A/N
BST CORBA/TAG PO Response Field	Address::driveInstructions
BST TAG PO Field Attr	175 A/N
Description	Driving Instructions — contains the directions used to identify and/or locate a particular unnumbered address
BST Firm Order Form	EU
BST Firm Order Field	SADLO (see comments)
BST Firm Order Field Attr	100 A/N
BST CORBA/TAG Order Field	lsr::SADLO (see comments)
BST TAG Order Field Attr	100 A/N
BST EDI Firm Order Field	SADLO (see comments)
Comments	SADLO is a concatenation of SERVICE-INSTRUC-TEXT + DRIVE-INSTRUCTIONS + DESC-LOC

**DUE DATE**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	DueDate::dueDate

BST TAG PO Field Attr	8 A/N
Description	Due Date — identifies the due date of the service/ product installation
BST Firm Order Form	LSR
BST Firm Order Field	DDD
BST Firm Order Field Attr	manual: 10 A/N w/2 pre-printed hypens electronic: 8 N
BST CORBA/TAG Order Field	LSR::ddd
BST TAG Order Field Attr	8 N
BST EDI Firm Order Field	DDD
Comments	CCYYMMDD; if a submitted due date is earlier than can be met, the msgld will be returned with a “001” in it and will ask you to resubmit the inquiry with a later due date

**EFF-DT**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::featureEffectiveDate
BST TAG PO Field Attr	8 A/N
Description	Feature Effective Date — identifies the date a feature will become available in the switch
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Format is CCYYMMDD



**ELEV-FLOOR**

BST PO Field Attr	14 A/N
BST CORBA/TAG PO Response Field	Address::Floor
BST TAG PO Field Attr	14 A/N
Description	Floor — identifies the floor number within the building of the end street address
BST Firm Order Form	EU
BST Firm Order Field	EU-FLOOR
BST Firm Order Field Attr	Manual: 4 A/N Electronic: 12 A//N
BST CORBA/TAG Order Field	EULocationAndAccess::euFloor
BST TAG Order Field Attr	12 A/N
BST EDI Firm Order Field	FLOOR-EU
Comments	

**EST-SERVICE-DATE**

BST PO Field Attr	8 N
BST CORBA/TAG PO Response Field	Service Restriction Info::estServiceDate
BST TAG PO Field Attr	8N
Description	Estimated Service Date — expected date on which the service will be available (or, when the restriction will no longer apply)
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	Format is CCYYMMDD
<b>EXIST-MLH-NO</b>	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	terminalCode
BST TAG PO Field Attr	5 A/N
Description	Existing Multi-Line Hunt Group — identifies the existing hunt group number of a multi-line hunt arrangement
BST Firm Order Form	LSR
BST Firm Order Field	HID?
BST Firm Order Field Attr	1 or 4 A or up to 3 N
BST CORBA/TAG Order Field	LSRHuntGroupIdentification::hid
BST TAG Order Field Attr	4 A/N
BST EDI Firm Order Field	HID
Comments	
<b>EXT-FEATURE-NAME</b>	
BST PO Field Attr	25 A/N
BST CORBA/TAG PO Response Field	productName or featureTitle — ask Gloria per DeRay
BST TAG PO Field Attr	25 A/N
Description	Feature Name — identifies the feature name associated with the USOC
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**FACAVAIL**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	ServiceAddressTelephoneInfo::availableFacilitiesIndicator
BST TAG PO Field Attr	1 A/N

Description	Service Address Available Facilities Indicator — indicates availability of facilities at a specified address
-------------	--

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Order Field	N/A

Comments

**FEATURE-TITLE**

BST PO Field Attr	25 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::featureTitle
BST TAG PO Field Attr	25 A/N

Description	Feature Title — identifies the feature title of the product
-------------	---

BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**HOUSE-NUM**

BST PO Field Attr	18 A/N
BST CORBA/TAG PO Response Field	Address::HouseNumber
BST TAG PO Field Attr	18 A/N

Description	Service Address House Number — identifies the house number of the service address
-------------	---

BST Firm Order Form	EU
BST Firm Order Field	SANO
BST Firm Order Field Attr	8 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sano
BST TAG Order Field Attr	8 A/N
BST EDI Firm Order Field	SANO

Comments

**HOUSE-NUM-HI**

BST PO Field Attr	13 A/N
BST CORBA/TAG PO Response Field	HouseNumberRange::toHouseNumber
BST TAG PO Field Attr	13 A/N

Description	Street Range High House Number — identifies the high range of house numbers on a specified street
-------------	---

BST Firm Order Form	N/A
---------------------	-----

BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**HOUSE-NUM-LOW**

BST PO Field Attr	13 A/N
BST CORBA/TAG PO Response Field	HouseNumberRange::from HouseNumber
BST TAG PO Field Attr	13 A/N
Description	Street Range Low House Number — identifies the low range of house numbers on the specified street name

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments N/A on CORBA order side per Steve Huff 2/7

**HOUSE-NUM-SUFFIX**

BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	Address::HouseNumberSuffix
BST TAG PO Field Attr	5 A/N

Description	Service Address House Number Suffix — identifies the suffix for the house number of the service address (i.e. “1/2”)
BST Firm Order Form	EU
BST Firm Order Field	SASF
BST Firm Order Field Attr	5 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sasf
BST CORBA Order Field Attr	5 A/N
BST EDI Order Field	SASF
Comments	
<b>HUNT-GRP-NUM1</b>	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	HuntGroupNumber::huntGroupNumber
BST TAG PO Field Attr	5 A/N
Description	Hunt Group Number — identifies the hunt group number associated with a multi-line hunt arrangement
BST Firm Order Form	LSR
BST Firm Order Field	HID
BST Firm Order Field Attr	1 or 4 A or up to 3 N
BST CORBA/TAG Order Field	LSRHuntGroupIdentification::hid
BST TAG Order Field Attr	4 A/N

BST EDI Firm Order Field

HID

Comments

**HUNT-GRP-NUM2**

BST PO Field Attr

5 A/N

BST CORBA/TAG PO Response Field

HuntGroupNumber::huntGroupNumber

BST TAG PO Field Attr

5 A/N

Description

Hunt Group Number — identifies the hunt group number associated with a multi-line hunt arrangement

BST Firm Order Form

N/A

BST Firm Order Field

N/A

BST Firm Order Field Attr

N/A

BST CORBA/TAG Order Field

N/A

BST TAG Order Field Attr

N/A

BST EDI Firm Order Field

N/A

Comments

**ICO-IND**

BST PO Field Attr

1 A/N

BST CORBA/TAG PO Response Field

Address::companyIndicator

BST TAG PO Field Attr

1 A/N

Description

Independent Company Indicator — if populated with “Y”, indicated the specified address is not within BellSouth territory

BST Firm Order Form

N/A

BST Firm Order Field

N/A

BST Firm Order Field Attr

N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Order Field	N/A

Comments

**INQ-NUM**

BST PO Field Attr	16 A/N
BST CORBA/TAG PO Response Field	Inquiry Number
BST CORBA PO Field Attr	16 A/N

Description	Inquiry Number - identifies the customer provided tracking number to link the inquiry with the response
-------------	---

BST Firm Order Form	<ul style="list-style-type: none"><li>• LSR</li><li>• LSR-HGI</li><li>• EU</li><li>• DL</li><li>• DSCR</li><li>• LS</li><li>• LSNP</li><li>• NP</li><li>• RS</li><li>• PS</li></ul>
---------------------	---

BST Firm Order Field	PON
BST Firm Order Field Attr	16 A/N
BST CORBA/TAG Order Field	LSR::pon
BST TAG Order Field Attr	16 A/N
BST EDI Firm Order Field	PON

Comments	NOTE: INQ_NUM may, but doesn't necessarily, map to the firm order PON field.
----------	--



**IN-TER-RANGE1**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	HuntGroupNumber::inTerminalRange
BST TAG PO Field Attr	8 A/N
Description	In Terminal Range — identifies the range of the Inward Ters
BST Firm Order Form	LSR
BST Firm Order Field	HID
BST Firm Order Field Attr	1 or 4 A or up to 3 N
BST CORBA/TAG Order Field	LSRHuntGroupIdentification::hid
BST TAG Order Field Attr	4 A/N
BST EDI Firm Order Field	HID
Comments	

**IN-TER-RANGE2**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	HuntGroupNumber::inTerminalRange
BST TAG PO Field Attr	8 A/N
Description	In Terminal Range 2 — identifies the range of the Inward Ters
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
<b>ISDN-IND</b>	
BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	SwitchInfo::isdnIndicator
BST TAG PO Field Attr	1 A/N
Description	ISDN Indicator — indicates if the switch is an ISDN switch
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>LAST-IN-TER</b>	
BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	lastInTerminal
BST TAG PO Field Attr	4 A/N
Description	Last In Terminal — identifies the last Inward Ter number in an existing multi-line hunt arrangement
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**LAST-OUT-TER**

BST PO Field Attr 4 A/N

BST CORBA/TAG PO Response Field lastOutTerminal

BST TAG PO Field Attr 4 A/N

Description Last Out Terminal — identifies the last Outward Ter number in an existing multi-line hunt arrangement

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field

Comments

**LEAD-TN**

BST PO Field Attr 10 A/N

BST CORBA/TAG PO Response Field HuntGroupNumber::leadTelephoneNumber

BST TAG PO Field Attr 10 A/N

Description Lead Telephone Number — identifies the lead telephone number in a multi-line hunt arrangement

BST Firm Order Form

- LSR
- RS

BST Firm Order Field TLI

BST Firm Order Field Attr	10N
BST CORBA/TAG Order Field	LSRHuntGroupIdentification::tli
BST TAG Order Field Attr	10N
BST EDI Firm Order Field	TLI

Comments

**LSO-NPA-TTA**

BST PO Field Attr	6N
BST CORBA/TAG PO Response Field	Alternative AddressInfo::npanxx
BST TAG PO Field Attr	6N

Description Local Serving Office — Numbering Planning Administration — Terminating Traffic Area — geographic zone where a specific group of telephone numbers have been allocated to subscribers

BST Firm Order Form	LSR
BST Firm Order Field	LSO
BST Firm Order Field Attr	6 N
BST CORBA/TAG Order Field	LSR::lso
BST TAG Order Field Attr	11 N
BST EDI Firm Order Field	LSO

Comments

**LST**

BST PO Field Attr	11 A/N
BST CORBA/TAG PO Response Field	Alternative AddressInfo::localServiceTermination
BST TAG PO Field Attr	11 A/N

Description	Local Service Termination — identifies the CLLI code of the end office switch from which service is being provided
BST Firm Order Form	LSR
BST Firm Order Field	LST
BST Firm Order Field Attr	11 A/N
BST CORBA/TAG Order Field	LSR::lst
BST TAG Order Field Attr	11 A/N
BST EDI Firm Order Field	LST

Comments

**MLGH-LEAD-TN1**

BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	HuntGroupNumber::leadTelephoneNumber
BST TAG PO Field Attr	10 A/N

Description Multil-Line Hunt Lead Telephone Number — identifies the lead telephone number

BST Firm Order Form	<ul style="list-style-type: none"> <li>• LSR</li> <li>• RS</li> </ul>
BST Firm Order Field	TLI
BST Firm Order Field Attr	10 N
BST CORBA/TAG Order Field	LSRHuntroupidentification::tli
BST TAG Order Field Attr	10N

BST EDI Firm Order Field	TLI
Comments	
<b>MLGH-LEAD-TN2</b>	
BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	HuntGroupNumber::leadTelephoneNumber
BST TAG PO Field Attr	10 A/N
Description	Multi—Line Hunt Lead Telephone Number 2 — identifies the lead telephone number
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>MSG-ID</b>	
BST PO Field Attr	14 A/N
BST CORBA/TAG PO Response Field	Status::msgld
BST TAG PO Field Attr	14 A/N
Description	Message ID — contains the address validation transaction message code for the condition encountered as a result of inquiry processing
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**MSG-TEXT**

BST PO Field Attr	264 A/N
BST CORBA/TAG PO Response Field	Status ::msgTxt
BST TAG PO Field Attr	264 A/N

Description	Message Text — contains the address validation transaction message text, corresponding to the MSG-ID, pertaining to the inquiry output
-------------	--

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**NEWINST1-2**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialNewinstall 1-2
BST TAG PO Field Attr	2 A/N

Description	New Install 1-2 Interval — Interval for residential new install with 1 or 2 lines
-------------	---

BST Firm Order Form	N/A
---------------------	-----

**Pre-Order to Firm Order Mapping Matrix  
Pre-Order Response Field**

**CG-MAPP-001  
Issue 1, February, 2001**

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**NEWINST3**

BST PO Field Attr 2 A/N

BST CORBA/TAG PO Response Field Interval::newinstall 3

BST TAG PO Field Attr 2 A/N

Description New Install 3 Interval — Interval to add 3 new residential lines

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**NEWINST4**

BST PO Field Attr 2 A/N

BST CORBA/TAG PO Response Field Interval::newinstall4

BST TAG PO Field Attr 2 A/N

Description New Install 4 Interval — Interval to add 4 new residential lines



BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**NEWINST5**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::newinstall5
BST TAG PO Field Attr	2 A/N
Description	New Install 5 Interval — Interval to add 5 new residential lines
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**NEWINST6-10**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialNewinstall6-10
BST TAG PO Field Attr	2 A/N

Description	New Install 6–10 Interval — Interval to add 6–10 new residential lines
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**NEWINST11–15**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialNewinstall11–15
BST TAG PO Field Attr	2 A/N

Description New Install 11–15 Interval — Interval to add 11–15 new residential lines

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**NEWINST1–2–BUS**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialNewinstall11–2

BST TAG PO Field Attr	2 A/N
Description	New Install 1-2 Business interval — Interval for business new install with 1 or 2 lines
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ODD-EVEN-IND**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AddressWithRange::oddEvenIndicator
BST TAG PO Field Attr	1 A/N
Description	Street Range Odd/Even Indicator — indicates whether the street numbers in a range are odd, even, or both
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field N/A

Comments

**OUT-TER-RANGE1**

BST PO Field Attr 8 A/N

BST CORBA/TAG PO Response Field HuntGroupNumbers:: outTerminalRange

BST TAG PO Field Attr 8 A/N

Description Out Terminal Range — identifies the range of the Outward Ters

BST Firm Order Form LSR

BST Firm Order Field HT

BST Firm Order Field Attr 15 A/N

BST CORBA/TAG Order Field LSRHuntDetail::ht

BST TAG Order Field Attr 15 A/N

BST EDI Firm Order Field HT

Comments

**OUT-TER-RANGE2**

BST PO Field Attr 8 A/N

BST CORBA/TAG PO Response Field HuntGroupNumber::outTerminalRange

BST TAG PO Field Attr 8 A/N

Description Out Terminal Range 2 — identifies the range of the Outward Ters

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field

BST EDI Order Field Attr

OBF Order Form N/A

OBF Order Field N/A

OBF Order Field Attr N/A

Comments

**PRODUCT-ID**

BST PO Field Attr 6 A/N

BST CORBA/TAG PO Response Field ProductFeatureInfo::productId

BST TAG PO Field Attr 6 A/N

Description Product ID (Service Abbreviation) — identifies the system abbreviation for the service/feature

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PRODUCT-NAME**

BST PO Field Attr 25 A/N

BST CORBA/TAG PO Response Field ProductFeatureInfo::productName

BST TAG PO Field Attr 25 A/N

Description	Product Name — identifies the full service name of the product
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**PV-FRI1**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	AppointmentData::pvAvailability
BST TAG PO Field Attr	1 A/N

Description PV Appointment Availabililty Status Code for FRI1 — provides premise visit availability for Friday

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**PV-REINST**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::pvResidentialReinstall

BST TAG PO Field Attr	2 A/N
Description	PV Re-Install Interval — Interval For Residential Re-Install with PV
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>PV-REINST-BUS</b>	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::pvBusinessReinstall
BST TAG PO Field Attr	2 A/N
Description	PV Re-Install Business Interval — interval for business re-install with PV
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field N/A

Comments

**PV-SAT1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for SAT1 — provides premise visit availability for Saturday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PV-SUN1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for SUN 1 — provides premise visit availability for Sunday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A



BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PV-MON1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for Mon1 — provides premise visit availability for Monday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PV-THU1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for THU1 — provides premise visit availability for Thursday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PV-TUE1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for TUE1 — provides premise visit availability for Tuesday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr N/A

BST CORBA/TAG Order Field N/A

BST TAG Order Field Attr N/A

BST EDI Firm Order Field N/A

Comments

**PV—WED1**

BST PO Field Attr 1 A/N

BST CORBA/TAG PO Response Field AppointmentData::pvAvailability

BST TAG PO Field Attr 1 A/N

Description PV Appointment Availability Status Code for WED1 — provides premise visit availability for Wednesday

BST Firm Order Form N/A

BST Firm Order Field N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**QTY-IN-TER**

BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	validate TNAQ_MLH::quantityInTerminals
BST TAG PO Field Attr	4 A/N
Description	In Terminal Quantity — identifies the quantity of Inward Ters

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**QTY-OUT-TER**

BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	validateTNAQ_MLH::quantityOutTerminals
BST TAG PO Field Attr	4 A/N
Description	Out Terminal Quantity — identities the quantity of Outward Ters

BST Firm Order Form	N/A
---------------------	-----



Description	Quick Service Interval — Interval for quick service
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**QUICK-SERV-IND**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	ServiceAddressTelephoneInfor::quickServeIndicator
BST TAG PO Field Attr	1 A/N

Description Telephone Number Quick Serve Indicator — if populated with a “Y”, indicates a “warm line” which provides dial tone for calls to E911 services

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**RATE-ZONE**

BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	Address::rateZone

BST TAG PO Field Attr	5 A/N
Description	Rate Zone — identifies the mileage zone code applicable to the specified address
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	N/A on CORBA order side per Steve Huff 2/7
<b>REINST-3</b>	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::reinstall3
BST TAG PO Field Attr	2 A/N
Description	Re-Install 3 Interval — Interval for re-install of 3 or more lines
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
<b>REQNUM</b>	
BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	See Comments
BST TAG PO Field Attr	10 A/N
Description	Requested Number(s) — identifies the telephone number(s) returned
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	See comments
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	The REQNUM is an input parameter only. It is not “returned” by TAG. Rather, across the board in TAG, the input structures populated by the CLEC application prior to a TAG method call are guaranteed to remain unchanged at the time of return from the method; therefore all input values are still available to the CLEC application at the end of a TAG method call.
<b>RES-IW</b>	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialInsideWire
BST TAG PO Field Attr	2 A/N
Description	Residential Inside Wire Interval — Interval for residential unregulated, inside wire, other
BST Firm Order Form	N/A

BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**ROUTE**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::route
BST TAG PO Field Attr	2 A/N

Description Postal Route — identifies the postal route of the end user's location

BST Firm Order Form	EU
BST Firm Order Field	SATH
BST Firm Order Field Attr	10 A/N
BST CORBA/TAG Order Field	SATH
BST TAG Order Field Attr	10 A/N
BST EDI Firm Order Field	SATH

Comments

**SERVICE-INSTRUC-TEXT**

BST PO Field Attr	4097 A/N
BST CORBA/TAG PO Response Field	AddressInfoHeader::ServiceInstructionText
BST TAG PO Field Attr	4097 A/N



Description	Service Instructions Text — textual description of special instructions necessary to provide service for the specified address
BST Firm Order Form	EU
BST Firm Order Field	SADLO (see comments)
BST Firm Order Field Attr	100 A/N
BST CORBA/TAG Order Field	lsr::sadlo (see comments)
BST TAG Order Field Attr	100 A/N
BST EDI Firm Order Field	SADLO (see comments)
Comments	SADLO is a concatenation of SERVICE-INSTRUC-TEXT + DRIVE-INSTRUCTIONS + DESC-LOC

**STATE**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::state
BST TAG PO Field Attr	2 A/N
Description	Service Address State/Province — identifies the state/province where the service is located
BST Firm Order Form	EU
BST Firm Order Field	EU-STATE
BST Firm Order Field Attr	2A
BST CORBA/TAG Order Field	EULocatonAndAccessHeader::euState
BST TAG Order Field Attr	2A

BST EDI Firm Order Field	STATE-EU
Comments	
<b>STREET-DIR</b>	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::StreetDirectional
BST TAG PO Field Attr	2 A/N
Description	Service Address Street Directional — identifies the street directional of the service address (i.e. “NE”)
BST Firm Order Form	EU
BST Firm Order Field	SASD
BST Firm Order Field Attr	2 A
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sasd
BST TAG Order Field Attr	2 A/N
BST EDI Firm Order Field	SASD
Comments	LENS response name is “Dir-Prefix”
<b>STREET-NAME1</b>	
BST PO Field Attr	44 A/N
BST CORBA/TAG PO Response Field	Address::StreetName
BST TAG PO Field Attr	44 A/N
Description	Service Address Street Name — identifies the street name of the service address (i.e. “Main”)
BST Firm Order Form	EU
BST Firm Order Field	SASN
BST Firm Order Field Attr	50 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sasn

BST TAG Order Field Attr 50 A/N

BST EDI Firm Order Field SASN

Comments

**STREET-SUFFIX**

BST PO Field Attr 4 A/N

BST CORBA/TAG PO Response Field Address::StreetSuffix

BST TAG PO Field Attr 4 A/N

Description Service Address Street Suffix — identifies the suffix of the street service address (i.e. “NW”)

BST Firm Order Form EU

BST Firm Order Field SASS

BST Firm Order Field Attr 4 A/N

BST CORBA/TAG Order Field EULocationAndAccessHeader::sass

BST TAG Order Field Attr 4 A/N

BST EDI Firm Order Field SASS

Comments

**STRUC-BLDG**

BST PO Field Attr 14 A/N

BST CORBA/TAG PO Response Field Address::Building

BST TAG PO Field Attr 14 A/N

Description Building — identifies the building located at the street address

BST Firm Order Form EU

BST Firm Order Field EU-BLDG

BST Firm Order Field Attr 9 A/N

BST CORBA/TAG Order Field	EULocationAnIdAccess::euBldg
BST TAG Order Field Attr	15A
BST EDI Firm Order Field	BLDG-EU

Comments

**SWITCH-TYPE**

BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	SwitichInfo::switchType
BST TAG PO Field Attr	4 A/N

Description Switch Type — identifies the type of switch in which the service is found

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TARIFF-EFF-DT**

BST PO Field Attr	8 N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::tariffEffectiveDate
BST TAG PO Field Attr	8 N

Description Tariff Effective Date — identifies the date a feature will become effective in the tariff

BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Format CCYYMMDD

**TARIFF-EXCHANGE-CODE**

BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	AreaTransferInfo:TraiffExchangeCode
BST TAG PO Field Attr	4 A/N
Description	Tariff Exchange Code — telephone company defined standard abbreviation for a tariff exchange name
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	

**TARIFF-NOTES**

BST PO Field Attr	65 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::tariffNotes
BST TAG PO Field Attr	65 A/N
Description	Tariff Notes — identifies any tariff notes associated with the service abbreviation
BST Firm Order Form	N/A

BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TARIFF-STATUS**

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::tariffStatus
BST TAG A PO Field Attr	2 A/N
Description	Tariff Statuses — identifies the current status of the service abbreviation in the tariff
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TEXT**

BST PO Field Attr	395 A/N
BST CORBA/TAG PO Response Field	ServiceRestrictionInfo::restrictionText
BST TAG PO Field Attr	395 A/N

Description	Service RestrictionText — text associated with the restriction code, which identifies some limitation of service at a given address
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TEXT-CODE**

BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	ServiceRestrictionInfo::restrictionCode
BST TAG PO Field Attr	5 A/N

Description	Service Restriction Text Code — ID code for a restriction
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
<b>THOROUGHFARE</b>	
BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	Address::StreetThoroughfare
BST TAG PO Field Attr	10 A/N
Description	Service Address Street Thoroughfare — identifies the thoroughfare portion of the street name of the service (i.e. “Road”)
BST Firm Order Form	EU
BST Firm Order Field	SATH
BST Firm Order Field Attr	10 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sath
BST TAG Order Field Attr	10 A/N
BST EDI Firm Order Field	SATH
Comments	
<b>TN</b>	
BST PO Field Attr	40 A/N
BST CORBA/TAG PO Response Field	TelephoneNumber
BST TAG PO Field Attr	40 A/N
Description	Working Telephone Number(s) — Identifies the working telephone numbers at the end user’s location
BST Firm Order Form	<ul style="list-style-type: none"> <li>• RS</li> <li>• PS</li> </ul>
BST Firm Order Field	TNS
BST Firm Order Field Attr	17 A/N including 2 preprinted hyphens



BST CORBA/TAG Order Field                      RSServiceDetail::tns or PORTService Detail::tns,  
depending on form

BST TAG Order Field Attr                      15 A/N

BST EDI Firm Order Field                      TNS

Comments

**TN-OPT-ASCCON**

BST PO Field Attr                              1 A/N

BST CORBA/TAG PO Response Field              TNOptions

BST TAG PO Field Attr                      1A/N

Description                                      TN Option Ascending — identifies if the telephone  
number(s) returned is ascending

BST Firm Order Form                              N/A

BST Firm Order Field                              N/A

BST Firm Order Field Attr                      N/A

BST CORBA/TAG Order Field                      N/A

BST TAG Order Field Attr                      N/A

BST EDI Firm Order Field                      N/A

Comments

**TN-OPT-COIN**

BST PO Field Attr                              1 A/N

BST CORBA/TAG PO Response Field              TNOptions

BST TAG PO Field Attr                      1 A/N

Description                                      TN Option Coin — identifies if the telephone  
number(s) returned is coin

BST Firm Order Form                              N/A?

BST Firm Order Field	N/A?
BST Firm Order Field Attr	N/A?
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TN-OPT-DSCCON**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG A PO Field Attr	1 A/N

Description TN Option Descending — identifies if the telephone number(s) returned is descending

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TN-OPT-EASY**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1A/N

Description TN Option Easy – identifies if the telephone number(s) returned is easy

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TN-OPT-IDENT**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1 A/N

Description TN Option Identical — identifies if the telephone number(s) returned is identical

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TN-OPT-SEQLINE**

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1 A/N

Description	TN Option Sequential — identifies if the telephone number(s) returned is sequential
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**TOSOFG**

BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	Carrier Info::serviceOfferingType
BST TAG PO Field Attr	8 A/N

Description Type of Service Offering — identifies the type of service offered by the carrier

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

**UNIT-ROOM**

BST PO Field Attr	15 A/N
BST CORBA/TAG PO Response Field	Address::room

BST TAG PO Field Attr	15 A/N
Description	Room — identifies the room of the end user's location (i.e. "Slip 4" or "Apt 4" )
BST Firm Order Form	EU
BST Firm Order Field	EU-ROOM
BST Firm Order Field Attr	Manual: 9 A/N Electronic: 15 A/N
BST CORBA/TAG Order Field	EULocationAndAccess::euRoom
BST TAG Order Field Attr	15A/N
BST EDI Firm Order Field	ROOM-EU

Comments

**USOC**

BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::productFeatureUsocList
BST TAG PO Field Attr	5 A/N
Description	Uniform Service Order Code — identifies the USOC associated with the service abbreviation
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	NA/
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
<b>WATS-SERV-OFF</b>	
BST PO Field Attr	11 A/N
BST CORBA/TAG PO Response Field	SwitchInfo::watsServingOffice
BST TAG PO Field Attr	11 A/N
Description	WATS Serving Office — identifies if the switch is a SATS switch
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
<b>XBOUND-STATE</b>	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::crossBoundary
BST TAG PO Field Attr	2 A/N
Description	City Cross Boundary State — any situation in which a defined telephone serving area, such as a wire center or community, crosses a defined boundary such as a state line
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	The data in this field should be the state code (i.e. "GA" for Georgia).
<b>ZIP-CODE</b>	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	Address::zipCode
BST TAG PO Field Attr	5 A/N
Description	Service Address Zip Code — identifies the zip code or postal code of the service address
BST Firm Order Form	EU
BST Firm Order Field	EU-ZIP CODE
BST Firm Order Field Attr	Manual: 5 A/N or 10 A/N Electronic: 5 A/N or 9 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::euZipCode
BST TAG Order Field Attr	9A/N
BST EDI Firm Order Field	ZIPCODE-EU
Comments	





**A. Scenario's**

**A.1 Scenario #1 – REQ TYP: M; ACT: C; Description: Change activity on residence port loop service adding block**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT107
N/A	VER	LSR	01
ATN	ATN	LSR	7705550974
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991217
DUE DATE	DDD	LSR	19991231
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C
N/A	CC	LSR	8003
LSO-NPA-TTA	LSO	LSR	770555
N/A	TOS	LSR	2BF
N/A	CIC	LSR	5124
N/A	BAN1	LSR	404Q8480003003
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JANE DOE
N/A	IMPCON-TEL-NO	LSR	4045557112
N/A	LOCNUM	EU	000
N/A	EU-NAME	EU	MAMA ROSE BELL
HOUSE-NUM	SANO	EU	525

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
STREET-DIR	SASD	EU	N
STREET-NAME1	SASN	EU	MAIN
THOROUGHFARE	SATH	EU	ST
CITY	EU-CITY	EU	ALPH
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30004
N/A	PQTY	PS	001
N/A	BA	PS	A
N/A	BLOCK	PS	C
N/A	LNA	PS	C
N/A	LNUM	PS	00001
TN	TNS	PS	7705550974

**A.2 Scenario #2 – REQ TYP: M; ACT: C; Description: Change activity to port loop business service with phone number change and no transfer of calls**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT65
ATN	ATN	LSR	9125552405
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991217
DUE DATE	DDD	LSR	19991221
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CC	LSR	8002
LSO-NPA-TTA	LSO	LSR	912555
N/A	TOS	LSR	1BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	706Q8580002002
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JANE DOE
N/A	IMPCON-TEL-NO	LSR	4045557112
N/A	LOCNUM	EU	000
N/A	EU-NAME	EU	FLOWER SHOP INC
HOUSE-NUM	SANO	EU	304
STREET-NAME1	SASN	EU	PINE
THOROUGHFARE	SATH	EU	AV
CITY	EU-CITY	EU	ALBY
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	31701
N/A	PQTY	PS	001
N/A	LNA	PS	X
N/A	LNUM	PS	00001
N/A	OTN	PS	9125557064
N/A	TC OPT	PS	NO
TN	TNS	PS	9125552405

**A.3 Scenario #3 – REQ TYP: M; ACT: C; Description: Change activity on residential port loop service deleting block, changing PIC, and adding PIC freeze**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT71
ATN	ATN	LSR	7705550668
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991216
DUE DATE	DDD	LSR	19991230
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C
N/A	CC	LSR	8002
LSO-NPA-TTA	LSO	LSR	770555
N/A	TOS	LSR	2BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	770Q895733733
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JEAN DOE
N/A	IMPCON-TEL-NO	LSR	4045557374
N/A	EU-NAME	EU	JEANIE DREAMER
HOUSE-NUM	SANO	EU	5375
STREET-NAME1	SASN	EU	CHAMBLEE DUNWOODY
THOROUGHFARE	SATH	EU	RD
CITY	EU-CITY	EU	DUN

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30338
N/A	PQTY	PS	001
N/A	BA	PS	D
N/A	BLOCK	PS	H
N/A	LNA	PS	C
N/A	LNUM	PS	00001
N/A	LPIC	PS	NC
N/A	PIC	PS	0288
TN	TNS	PS	7705550668

**A.4 Scenario #4 – REQ TYP: M; ACT: N; Description: New installation of port loop combo residence service with block and working service on premises (WSOP)**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT23-A
ATN	ATN	LSR	4045550312
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	2000114
DUE DATE	DDD	LSR	20000131
N/A	APPTIME-DDD	LSR	0900-1300
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	N
N/A	CC	LSR	8002

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	PORTTYP	LSR	L
LSO-NPA-TTA	LSO	LSR	404555
N/A	TOS	LSR	1BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	404Q858002002
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	LAURA DOE
N/A	IMPCON-TEL-NO	LSR	4045557375
N/A	EU-NAME	EU	DADDY MAX
HOUSE-NUM	SANO	EU	969
STREET-NAME1	SASN	EU	OAK SPRINGS
THOROUGHFARE	SATH	EU	CT
CITY	EU-CITY	EU	ST MT
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30083
N/A	WSOP	EU	V
N/A	PQTY	PS	001
N/A	BA	PS	A
N/A	BLOCK	PS	H
N/A	LNA	PS	N
N/A	LNUM	PS	00001
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	4045550312

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2R
N/A	DLNUM	DL	0001
N/A	LACT	DL	N
N/A	RTY	DL	LML
N/A	LTY	DL	1
N/A	STYC	DL	SL
N/A	TOA	DL	R
N/A	DOI	DL	0
N/A	LTN	DL	4045550312
N/A	LNLN	DL	MAX
N/A	LNFN	DL	DADDY
N/A	LANO	DL	969
N/A	LASN	DL	OAK SPRINGS
N/A	LATH	DL	CT
N/A	LALOC	DL	ST MT
N/A	LAST	DL	GA

**A.5 Scenario #5 – REQ TYP: M; ACT: V; Description: Full conversion from multiline resale/retail account to port loop combo service; features are being added and/or deleted**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	ZXL
INQ-NUM	PON	LSR	FT120B
ATN	ATN	LSR	2285559485
N/A	SC	LSR	LCSC

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	D/SENT	LSR	19991222
DUE DATE	DDD	LSR	19991230
N/A	REQTYP	LSR	MB
N/A	ACT	LSR	V
N/A	CC	LSR	8002
N/A	PORTTYP	LSR	L
LSO-NPA-TTA	LSO	LSR	228555
N/A	TOS	LSR	1AM
N/A	CIC	LSR	5124
N/A	BAN1	LSR	E
N/A	INIT	LSR	FAY DOE
N/A	INIT-TEL-NO	LSR	2285557498
N/A	INIT-FAX-NO	LSR	2285557449
N/A	IMPCON	LSR	LAURA DOE
N/A	IMPCON-TEL-NO	LSR	2285557375
N/A	EU-NAME	EU	TIE FIGHTER
HOUSE-NUM	SANO	EU	243
STREET-DIR	SASD	EU	E
STREET-NAME1	SASN	EU	2ND
THOROUGHFARE	SATH	EU	ST
CITY	EU-CITY	EU	PASS CHRISTIAN
STATE	EU-STATE	EU	MS
ZIP-CODE	EU-ZIP CODE	EU	39571
N/A	ERL	EU	Y
N/A	EATN	EU	285559458
N/A	PQTY	PS	004

- continued -



- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	LNA	PS	V
N/A	LNUM	PS	00001
N/A	LOCNUM	PS	000
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	2285559458
N/A	FA	PS	N
N/A	FEATURE	PS	ESX
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2D
N/A	FA	PS	N
N/A	FEATURE	PS	TTB
N/A	LNA	PS	V
N/A	LNUM	PS	00002
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	2285554583
N/A	FA	PS	N
N/A	FEATURE	PS	TTB
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2D
N/A	LNA	PS	V
N/A	LNUM	PS	00004
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	2285559194

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	FA	PS	N
N/A	FEATURE	PS	TTB
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2D
N/A	LNA	PS	V
N/A	LNUM	PS	00002
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	2285553938
N/A	FA	PS	N
N/A	FEATURE	PS	BCR
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2D

**A.6 Scenario #6 – REQ TYP: M; ACT: V; Description: Full conversion from resale/retail account to port loop combo with block choices, “No Collect,” and no directory assistance call completion**

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT69RTST2
ATN	ATN	LSR	8645554765
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	20000108
DUE DATE	DDD	LSR	20000223
N/A	REQ TYP	LSR	MB

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	ACT	LSR	V
N/A	CC	LSR	8002
N/A	PORTTYP	LSR	L
LSO-NPA-TTA	LSO	LSR	864555
N/A	TOS	LSR	2BF
N/A	CIC	LSR	5124
N/A	BAN1	LSR	803Q895733733
N/A	INIT	LSR	KAREN DOE
N/A	INIT-TEL-NO	LSR	4045557493
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	KAREN DOE
N/A	IMPCON-TEL-NO	LSR	4045557493
N/A	DQTY	EU	000
N/A	EU-NAME	EU	BARNEY RUBBLE
HOUSE-NUM	SANO	EU	208
STREET-DIR	SASD	EU	S
STREET-NAME1	SASN	EU	BROAD
THOROUGHFARE	SATH	EU	ST
CITY	EU-CITY	EU	CLINTON
STATE	EU-STATE	EU	SC
ZIP-CODE	EU-ZIP CODE	EU	29325
N/A	ERL	EU	Y
N/A	EATN	EU	8645554765
N/A	PQTY	PS	001
N/A	BA	PS	A

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	BLOCK	PS	CH
N/A	LNA	PS	V
N/A	LNUM	PS	00001
TN	LPIC	PS	0288
N/A	PIC	PS	0288
N/A	TNS	PS	8645554765
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2R

A.7